

Exact solutions for reconnective annihilation in magnetic configurations with three sources

E. Tassi, V.S. Titov, and G. Hornig

*Theoretische Physik IV, Ruhr-Universität Bochum, 44780 Bochum, Germany**

(Dated: February 2, 2008)

Abstract

Exact solutions of the steady resistive three dimensional (3D) magnetohydrodynamics (MHD) equations in cylindrical coordinates for an incompressible plasma are presented. The solutions are translationally invariant along one direction and in general they describe a process of reconnective annihilation in a curved current layer with non vanishing magnetic field. In the derivation of the solutions the ideal case with vanishing resistivity and electric field is considered first and then generalized to include the effects of finite electric field and resistivity. Particular attention is devoted to the analysis how the latter ones influence the presence of singularities in the solutions. In this respect comparisons with the purely two-dimensional case are made and the resulting important differences are highlighted. Finally, applications of the solutions for modeling an important class of solar flares are discussed.

PACS numbers: 52.30, 96.60.R

Keywords: Exact solutions, MHD equations, magnetic reconnection, solar flares

I. INTRODUCTION

Magnetic reconnection is an effective mechanism for restructuring the magnetic field and converting magnetic energy into other forms of energy in plasmas with a high electric conductivity. This process plays a key role in large scale cosmic phenomena such as solar flares and geomagnetic substorms. Since the pioneering works of Dungey¹, Parker², Sweet³ and Petschek⁴, where the basic physics of magnetic reconnection was clarified, many exact two-dimensional (2D) solutions describing some simplified versions of this process were found^{5,6,7,8}.

Moreover, over the last few years there was a similar progress in the theory of three-dimensional (3D) reconnection. In particular, some simplified forms of this process at null points of 3D magnetic fields have been found as well^{9,10,11}.

In this paper we present a generalization of exact solutions for a 2D curvilinear geometry⁸, the so-called two and a half dimensions ($2\frac{1}{2}$ D) case, where a translational invariant component of velocity and magnetic field along the third direction exists. These solutions describe steady incompressible resistive magnetohydrodynamics (MHD) flows in a configuration with non-vanishing magnetic field. In some respects they resemble the 2D solutions describing a particular type of magnetic reconnection which is called reconnective annihilation⁷. So we will also use this term further on to denote the process described by our solutions.

It should be noted also that when the present article was in preparation, a paper of Watson and Craig¹² appeared, where similar solutions have been presented. Since we found these solutions independently, our considerations and interpretations differ in many respects.

In sections II and III, respectively, the basic equations and the form of solutions are described. In section IV we derive the solutions in the limit of ideal MHD and discuss their properties, while in section V we consider how these solutions are modified in the case of non-vanishing resistivity. The conclusions are drawn in section VI.

II. BASIC EQUATIONS

The set of MHD equations for an incompressible plasma with uniform density and resistivity consists of the equation of motion

$$(\mathbf{v} \cdot \nabla)\mathbf{v} = -\nabla p + (\nabla \times \mathbf{B}) \times \mathbf{B}, \quad (1)$$

the Ohm's law

$$\mathbf{E} + \mathbf{v} \times \mathbf{B} = \eta \nabla \times \mathbf{B} \quad (2)$$

and the divergence-free conditions for the velocity $\mathbf{v}$ and the magnetic field $\mathbf{B}$

$$\begin{aligned} \nabla \cdot \mathbf{v} &= 0, \\ \nabla \cdot \mathbf{B} &= 0. \end{aligned} \quad (3)$$

All equations here are written in a dimensionless form such that $\mathbf{B}$ and $\mathbf{v}$ are normalized to B_e and v_{Ae} respectively, which are characteristic values of the magnetic field and of the Alfvén velocity. $\mathbf{E}$ represents the dimensionless electric field while η corresponds to the inverse magnetic Reynolds number.

The current density $\mathbf{j}$ is determined separately by Ampère's law

$$\mathbf{j} = \nabla \times \mathbf{B}. \quad (4)$$

Consider a cylindrical coordinate system (r, θ, z) where r and θ are related to the Cartesian coordinates (x, y) in the following way

$$x = r \sin \theta, \quad y = r \cos \theta - d, \quad (5)$$

where $d > 0$ so that the pole is below the plane $y = 0$. Assume that in this coordinate system the functions $\mathbf{B}$ and $\mathbf{v}$ depend only on r and θ . Then they can be written as follows

$$(B_r, B_\theta, B_z) = \left(\frac{1}{r} \frac{\partial A}{\partial \theta}, -\frac{\partial A}{\partial r}, H \right), \quad (v_r, v_\theta, v_z) = \left(\frac{1}{r} \frac{\partial \psi}{\partial \theta}, -\frac{\partial \psi}{\partial r}, V \right), \quad (6)$$

where A , H , ψ and V are functions of r and θ which are to be found. In particular, for $H = V = 0$ this is the usual representation of two-dimensional magnetic and incompressible velocity fields in terms of a flux function A and a stream function ψ , respectively.

By using this representation we obtain from Eq. (1) that the functions A , H , ψ and V must satisfy the following two equations

$$[\psi, \nabla^2 \psi] = [A, \nabla^2 A], \quad (7)$$

$$[V, \psi] - [H, A] = Cr, \quad (8)$$

where C is an arbitrary constant and the Poisson brackets are used such that

$$[f, g] = \frac{\partial f}{\partial r} \frac{\partial g}{\partial \theta} - \frac{\partial g}{\partial r} \frac{\partial f}{\partial \theta}.$$

Similarly, Eq. (2) gives the following two equations

$$[H, \psi] + [A, V] = \eta r \nabla^2 H, \quad (9)$$

$$E_z r + [\psi, A] = -\eta r \nabla^2 A. \quad (10)$$

III. FORM OF THE SOLUTIONS

For the system (7)–(10) we seek solutions of the form

$$\begin{aligned} A(r, \theta) &= A_1(r)\theta + A_0(r), \\ \psi(r, \theta) &= \psi_1(r)\theta + \psi_0(r), \\ H(r, \theta) &= H_1(r)\theta + H_0(r), \\ V(r, \theta) &= V_1(r)\theta + V_0(r). \end{aligned} \quad (11)$$

This form is a generalization of the ansatz used in Ref. 8 for a two-dimensional configuration. Substituting (11) into (7)–(10) provides four equations each of which is a polynomial linear in θ . Thus for each equation the part of the polynomial not depending on θ and the coefficient of θ must be separately equal to 0. This yields the following set of ordinary differential equations (ODEs):

$$V_1 \psi_1' - V_1' \psi_1 - H_1 A_1' + H_1' A_1 = 0 \quad (12)$$

$$A_1 H_0' - H_1 A_0' + V_1 \psi_0' - \psi_1 V_0' = C r \quad (13)$$

$$\frac{\psi_1'}{r} (r \psi_1')' - \psi_1 \left[\frac{1}{r} (r \psi_1')' \right]' = \frac{A_1'}{r} (r A_1')' - A_1 \left[\frac{1}{r} (r A_1')' \right]' \quad (14)$$

$$\frac{\psi_0'}{r} (r \psi_1')' - \psi_1 \left[\frac{1}{r} (r \psi_0')' \right]' = \frac{A_0'}{r} (r A_1')' - A_1 \left[\frac{1}{r} (r A_0')' \right]' \quad (15)$$

$$A_1' V_1 - A_1 V_1' + \psi_1 H_1' - H_1 \psi_1' - \eta r H_1'' - \eta H_1' = 0 \quad (16)$$

$$V_1 A_0' + \psi_1 H_0' - A_1 V_0' - H_1 \psi_0' - \eta r H_0'' - \eta H_0' = 0 \quad (17)$$

$$\psi_1' A_1 - \psi_1 A_1' + \eta(A_1' + r A_1'') = 0 \quad (18)$$

$$E_z + \frac{1}{r}[\psi_0' A_1 - \psi_1 A_0' + \eta(A_0' + r A_0'')] = 0. \quad (19)$$

Here the prime stands for the derivative with respect to r . The above system consists of 8 ODEs for 8 unknowns of one variable. Therefore the ansatz (11) is compatible with the original system of partial differential equations. In our stationary case $\nabla \times \mathbf{E} = 0$, which together with Eq. (11) yields a uniform z -component of the electric field.

One can also notice that Eqs. (14), (15), (18) and (19) are the same as for the purely two-dimensional (2D) case corresponding to setting $H \equiv V \equiv 0$. Thus, the 2D equations are a limiting case of our $2\frac{1}{2}$ D case and, what is even more important, they are decoupled from the rest equations of the system. Solutions of Eq. (14), (15), (18) and (19) have already been presented in Ref. 12 and we can simply use these solutions for solving our more general problem. It is worth noticing that, for known A_1 , A_0' , ψ_1 and ψ_0' , the system of equations (12), (13), (16) and (17) is linear in the functions H_1 , H_0' , V_1 and V_0' .

IV. IDEAL SOLUTIONS

In this section Eqs. (12)–(19) are analyzed in the limit of vanishing resistivity $\eta = 0$. We start by considering the equipotential case, i.e. the case where the electric potential is constant along the z axis so that E_z vanishes as well. In this case, according to (10), $[\psi, A] = 0$ and (11) the relationship

$$\psi = \alpha A, \quad \alpha = \text{constant} \quad (20)$$

is valid. Eqs. (14), (15), (18) and (19) then yield

$$A_1 = C_1 \ln r + C_2, \quad \psi_1 = \alpha A_1, \quad (21)$$

$$A_0 = C_3 r^2 + C_4 \ln r, \quad \psi_0 = \alpha A_0, \quad (22)$$

where C_1 , C_2 , C_3 and C_4 are arbitrary constants. These solutions describe a magnetic configuration with a field-aligned flow in the (r, θ) plane. In this configuration there are one magnetic null point and one stagnation point, both are located at $\mathbf{r}^* = [r_c, -(2C_3 r_c^2 +$

$C_4)/C_1]$. Here $r_c \equiv \exp(-C_2/C_1)$ is denoted as a critical radius.

It is not difficult to see now that Eqs. (12) and (17) can be satisfied in the ideal limit by

$$V_1 = c_1 A_1, \quad H_1 = c_2 A_1, \quad (23)$$

where c_1 and c_2 are other arbitrary constants. Therefore V_1 and H_1 also vanish together with A_1 and ψ_1 at r_c . Then the evaluation of (13) at r_c requires $C \equiv 0$. Substituting of (23) into (13) and (17) yields

$$\begin{aligned} V_0 &= -\frac{c_1}{\alpha^2 - 1}(A_0 - \alpha\psi_0) - \frac{c_2}{\alpha^2 - 1}(\alpha A_0 - \psi_0) = c_1(C_3 r^2 + C_4 \ln r) + C_5, \\ H_0 &= -\frac{c_1}{\alpha^2 - 1}(\alpha A_0 - \psi_0) - \frac{c_2}{\alpha^2 - 1}(A_0 - \alpha\psi_0) = c_2(C_3 r^2 + C_4 \ln r) + C_6, \end{aligned} \quad (24)$$

where C_5 and C_6 are arbitrary constants.

Evaluating B_z and v_z at $\mathbf{r}^*$ we obtain

$$\begin{aligned} B_z|_{\mathbf{r}=\mathbf{r}^*} &= -2c_2 C_3 r_c^2 \left(\ln r_c - \frac{1}{2} \right) - \frac{2c_2 C_2}{C_1} \left(C_3 r_c^2 + \frac{C_4}{2} \right) + C_6, \\ v_z|_{\mathbf{r}=\mathbf{r}^*} &= -2c_1 C_3 r_c^2 \left(\ln r_c - \frac{1}{2} \right) - \frac{2c_1 C_2}{C_1} \left(C_3 r_c^2 + \frac{C_4}{2} \right) + C_5, \end{aligned} \quad (25)$$

which in general do not vanish. Therefore, contrary to the 2D case, in $2\frac{1}{2}$ D we generally have neither nulls nor stagnation points in the limit $E_z = \eta = 0$.

The velocity and magnetic field lines are presented in Fig. 1. They are superimposed on the distribution of the magnetic z component. The poloidal components (r, θ) and the nonuniform parts of the toroidal components (z) of our $\mathbf{v}$ and $\mathbf{B}$ are proportional to each other but generally with different coefficients of proportionality. This means that in our case the flow reshuffles the magnetic field lines inside each of the magnetic surfaces $A(r, \theta) = \text{constant}$ but it preserves the surfaces themselves. It can be noticed also that the distribution of magnetic flux can be imagined as generated by three sources with alternating polarities lying on the plane $y = 0$.

Consider now how the above ideal equipotential solution is modified in the presence of a finite z component of the electric field. In two dimensions it has been shown in Ref. 8 that a non-vanishing E_z causes the appearance of a singularity at $r = r_c$ in the current density, vorticity and azimuthal components of the magnetic and velocity fields. Indeed, one class of solutions can be written as follows

$$A_1 = C_1 \ln r + C_2, \quad \psi_1 = \alpha A_1, \quad (26)$$




FIG. 1: Magnetic (solid) and velocity (dashed) field lines superimposed on the distribution of the z component of the magnetic field shown in gray half-tones. The parameters used in the plot are $E_z = \eta = 0$, $r_c = 0.2$, $\alpha = 2$, $C_1 = 1.2$, $C_3 = 0.2$, $C_4 = -0.08C_3$, $C_2 = -C_1 \ln 0.2$, $C_6 = 1$, $c_2 = 0.8$, $d = 0.05$.

$$A_0' = \frac{\alpha}{\alpha^2 - 1} \frac{E_z r}{A_1} + \frac{a}{\alpha} r + \frac{b}{\alpha r}, \quad \psi_0' = \frac{1}{\alpha^2 - 1} \frac{E_z r}{A_1} + ar + \frac{b}{r}, \quad (27)$$

where a and b are arbitrary constants. From here one can see that the magnetic flux piles up at the separatrix $r = r_c$ to produce there the above mentioned singularity. Coming back to our $2\frac{1}{2}$ D problem, we notice that Eqs. (12), (13), (16) and (17) do not depend on E_z . Therefore the expressions (24) are still applicable for $E_z \neq 0$, if one uses for A_0' and ψ_0' the expressions (27). The solutions for V_1 , H_1 , V_0' and H_0' are then given by

$$V_1 = c_1 A_1, \quad H_1 = c_2 A_1, \quad (28)$$

$$H_0' = -\frac{c_1}{\alpha^2 - 1} \frac{E_z r}{A_1} + \frac{c_2}{\alpha} \left(ar + \frac{b}{r} \right), \quad V_0' = \frac{c_1}{\alpha} \left(ar + \frac{b}{r} \right) - \frac{c_2}{\alpha^2 - 1} \frac{E_z r}{A_1}. \quad (29)$$

These expressions show that, as in the 2D case, the presence of a non-vanishing E_z leads to the appearance of singularities in the distributions of physical values.

In particular, there is a singularity in the current density distribution (Fig. 2) as well as in the distributions of A_0' , ψ_0' , H_0' and V_0' . This means in turn that both the toroidal (z) and poloidal components of the current density become singular, which is also clear from




FIG. 2: Distribution of the current density $J \equiv |\mathbf{j}|$ in the case of $\eta = 0$ and finite E_z . The other used parameters in the plots are $c_1 = 0.5$, $c_2 = 0.4$, $r_c = 0.2$, $a = 0$, $b = 1$, $\alpha = 8/9$, $C_1 = -0.9/\ln 0.2$, $C_2 = 1$, $d = 0.05$.

their explicit expressions:

$$\begin{aligned} j_r &= \frac{H_1}{r}, \\ j_\theta &= -H'_1\theta - H'_0, \\ j_z &= -A'_0 - rA''_0. \end{aligned} \tag{30}$$

In other words, these $2\frac{1}{2}$ D solutions inherit the singularities from the corresponding 2D solutions although the interpretation of the inherited singularities compared to the original ones differs in several important respects.

As was shown above, the equipotential 2D magnetic configuration has a null point or, if one extends the system to three dimensions, a null line parallel to the invariant z direction. If an electric field $\mathbf{E}$ appears in the system, it may have just one z component due to the assumed two-dimensionality of the flow. The steadiness of the flow requires also that this electric field must be uniform. The latter implies in particular the presence of the electric field at the place where the null point (or null line) was initially located in the equipotential configuration. According to the frozen-in law condition, however, the finite value of $\mathbf{E}$ is sustained by the inductive field $-\mathbf{v} \times \mathbf{B}$ only. So, kinematically, the presence of $\mathbf{E} \neq \mathbf{0}$ at a magnetic null point would compel the velocity $\mathbf{v}$ to be infinite there. In our self-consistent

approach, incorporating both kinematics and dynamics of plasma, any velocity singularity may coexist only with an appropriate magnetic singularity, appearing at the same point in the result of the corresponding force balance. This is the reason why the magnetic null point of the equipotential configuration transforms into the proper magnetic singularity when passing in the considered family of exact 2D solutions to the configuration with a non-vanishing electric field.

The situation becomes different for our $2\frac{1}{2}$ D configurations, which generally have no longer null points. Therefore we cannot appeal to the above “null-point” argument to explain the origin of the inherited singularities. The desirable explanation in fact can be found considering the consequences of the presence of field lines with a finite longitudinal voltage drop¹³, denoted also as *singular magnetic field lines*¹⁴. Our $2\frac{1}{2}$ D equipotential configuration has in place of the null line a straight magnetic field line parallel to z axis. Passing to non-equipotential configurations in our family of solutions leads to the appearance of a constant z component of the electric field, which inevitably creates the above mentioned voltage drop along a straight magnetic field line. Kinematically, such a voltage drop in a plasma with an infinite conductivity may be sustained by a suitable velocity singularity only¹⁴. Our self-consistent consideration, incorporating plasma dynamics, shows that such a velocity singularity gives birth to an appropriate magnetic singularity by analogy with the 2D case. Thus, our stationary $2\frac{1}{2}$ D ideal MHD solutions provide a particular but explicit realization of singular magnetic field lines, whose properties were kinematically described first by Schindler et al.¹³ in a more general non-stationary case, where the voltage drop was localized at a finite part of such lines.

The above qualitative consideration shows that the appearance of singularities at the null line or singular magnetic field line can be anticipated if one combines the results of an analysis based on both the kinematics and the dynamics of a plasma. However, our explicit solutions reveal a much less obvious feature of this process, namely, that the singularity appears not only at the null or singular magnetic field lines but also at the whole magnetic separatrix surface $r = r_c$ containing such lines. In a more simple neutral X-type point configuration a similar fact follows from the frozen-in law and incompressibility conditions if one assumes also that the resulting plasma flow crosses one of the two separatrices and is parallel to the other¹⁵. These conditions are sufficient for the appearance of a singularity along the separatrix which is not crossed by the flow. The self-consistent incorporation of

the plasma dynamics just makes the type of such a singularity more precise. One can also see this from the ideal MHD limit of Craig-Henton solution⁶ and from the same limit of more general solutions⁷. It is not difficult to show that the considered point of view remains valid for our 2D and 2 $\frac{1}{2}$ D solutions in curvilinear geometry as well.

Thus, the above discussion suggests that the “extension” of the singularity from the null or singular field line to the whole separatrix surface is somehow effected by the incompressibility condition. This suggestion, however, looks not convincing enough if one remembers that in the three-dimensional case the velocity singularity at the fan separatrix surfaces of magnetic nulls appears already in a purely kinematic approach¹⁶ without any involvement of the incompressibility condition. So the complete clarification of the nature of the separatrix singularities is still a matter of the future development of the theory. Irrespective of the ultimate answer to this question, it is important to study how such singularities are resolved in the framework of a self-consistent MHD approach by a finite resistivity, which is an issue of the next section.

V. RESISTIVE SOLUTIONS

Let us now consider the complete system (12)–(19). For the functions A_1 , ψ_1 , A'_0 and ψ'_0 we can use the following solutions

$$A_1 = C_1 \ln r + C_2, \quad \psi_1 = \alpha A_1, \quad (31)$$

$$A'_0(r) = -\frac{\exp\left[\frac{-(\alpha^2-1)(C_1 \ln r + C_2)^2}{2\eta\alpha}\right]}{\eta r} \int_{r_c}^r \frac{E_z t - A_1 \frac{1-\alpha^2}{\alpha^2} (at + b/t) dt}{\exp\left[\frac{-(\alpha^2-1)(C_1 \ln t + C_2)^2}{2\eta\alpha}\right]}, \quad (32)$$

$$\psi'_0(r) = \frac{1}{\alpha} \left[A'_0(r) - \frac{1-\alpha^2}{\alpha} \left(ar + \frac{b}{r} \right) \right] \quad (33)$$

derived in Ref. 12. These solutions describe a 2D reconnective annihilation in a curved current layer formed on one of the magnetic separatrices when the other is crossed by a sheared flow. The magnetic and velocity fields have a null point and a stagnation point, respectively, whose positions, contrary to the case considered in Sec. IV, are in general not coincident. Considering now the 2 $\frac{1}{2}$ D problem, we first notice that Eqs. (28) are solutions

of the system for a finite resistivity as well. Therefore the problem is reduced to finding solutions for H'_0 and V'_0 . By means of Eq. (13) we can express V'_0 in the form

$$V'_0 = \frac{A_1 H'_0 - H_1 A'_0 + V_1 \psi'_0}{\psi_1} \quad (34)$$

which, with the help of (31) and (28), can be reduced to

$$V'_0 = \frac{1}{\alpha} (H'_0 - c_2 A'_0 + c_1 \psi'_0). \quad (35)$$

Inserting this expression into Eq. (17) and again using (31) and (28), we obtain the following equation

$$\eta r H''_0 + \left[\frac{(1 - \alpha^2)}{\alpha} A_1 + \eta \right] H'_0 + A_1 \left[\left(\frac{c_1}{\alpha} + c_2 \right) \psi'_0 - \left(\frac{c_2}{\alpha} + c_1 \right) A'_0 \right] = 0. \quad (36)$$

This linear equation can be solved by the method of the variation of parameters with the following result:

$$H'_0 = \left[\frac{1}{\alpha \eta r} \int ds (V_1 (\alpha A'_0 - \psi'_0) + H_1 (A'_0 - \alpha \psi'_0)) \right. \\ \left. \exp \left(-\frac{(\alpha^2 - 1)}{\eta \alpha} \int \frac{A_1}{t} dt \right) + c_5 \right] \exp \left(\frac{(\alpha^2 - 1)}{\eta \alpha} \int \frac{A_1}{s} ds \right). \quad (37)$$

By means of (28), (31) and (32) the solution (37) can be written as follows

$$H'_0 = \exp \left[\frac{-(\alpha^2 - 1)(C_1 \ln r + C_2)^2}{2\eta \alpha} \right] \left[\frac{1}{\alpha \eta r} \int ds \left(c_1 (\alpha^2 - 1) \left(\psi'_0 - as - \frac{b}{s} \right) \right. \right. \\ \left. \left. - c_2 \frac{\alpha^2 - 1}{\alpha} \left(as + \frac{b}{s} \right) \right) (C_1 \ln s + C_2) \exp \left(\frac{(\alpha^2 - 1)(C_1 \ln s + C_2)^2}{2\eta \alpha} \right) + c_5 \right]. \quad (38)$$

The resulting magnetic field configuration is represented in Fig. 3. The plot refers to the particular case where the line $(r = r_c, \theta = 0)$ is a magnetic null line. A more general configuration without this null line may be obtained by simply adding any constant value to the corresponding B_z distribution. This would give us an example of the resistive solution which in the limit of the ideal MHD describes the above mentioned configuration with singular magnetic field line.

In Fig. 4 the absolute value of the current density is plotted. Comparing this plot with the one shown in Fig. 2, one can see the effect of introducing a finite resistivity, which indeed resolves the singularity at the critical radius.




FIG. 3: Integral lines of the poloidal magnetic (in black) and velocity (in gray) fields, superimposed on the distribution of the z component of the magnetic field shown in gray half-tones. The parameters used for the plot are $\eta = 10^{-2}$, $E_z = 0.5$, $c_1 = 0.5$, $c_2 = 0.4$, $r_c = 0.2$, $a = 0$, $b = 1$, $\alpha = 8/9$, $C_1 = -0.9/\ln 0.2$, $C_2 = 1$, $d = 0.05$.




FIG. 4: Distribution of current density for the resistive case. The parameters used for this plot are the same used for the plot in fig. 3.

As already noticed in Ref. 8, the configuration of the magnetic field in the xy plane described by our resistive solutions is of particular interest for modeling the reconnection process in a special large class of solar flares. One can see from Fig. 3 that the magnetic field here is generated by three sources with alternating polarities on the plane $y = 0$. Observations¹⁷ show that a large fraction of solar flares occurs namely in configurations with three photospheric

magnetic sources. The $2\frac{1}{2}$ D solutions presented in this paper provide a generalization which makes the previous 2D model more realistic.

VI. CONCLUSIONS

We presented a class of steady solutions of resistive incompressible MHD equations in cylindrical coordinates. These solutions describe three-dimensional velocity and magnetic fields with a translational invariance along the z axis in a half-space corresponding to the solar corona. Both fields are represented as a superposition of poloidal and toroidal (z) components, so that the resulting fields have no null points in the volume. The poloidal fields, however, have one null line along which two separatrix surfaces intersect. One of the separatrices is the same for poloidal velocity and magnetic fields and it is a segment of cylinder with the edges at the photospheric boundary. The other separatrices are different and they intersect the cylindrical separatrix along the null lines of poloidal fields in such a way that these lines lie at some distance from each other. The resulting plasma flow intersects the non-cylindrical separatrix of the poloidal magnetic field to produce a strong shearing motion along the cylindrical separatrix, where a strong current layer is formed. Thus, our solution is a curvilinear analog of the planar reconnective magnetic annihilation considered earlier in Ref. 6 and generalized in Ref. 7. In addition to the curvature it has two more features of interest. First, there are non-vanishing and non-uniform toroidal components of the velocity and magnetic field in the corresponding configuration. Secondly, the resulting distribution of magnetic fields on the photosphere represents three areas of alternating polarities. This feature is very interesting for modeling a wide class of solar flares which have three photospheric magnetic sources of different polarities.

Acknowledgments

The authors would like to gratefully acknowledge the financial support from the Volkswagen-Foundation and from the E.U. Research Training Network HPRN-CT-2000-

* Electronic address: tassl@tp4.ruhr-uni-bochum.de

- ¹ J. Dungey, Philos. Mag. **7**, 725 (1953).
- ² E. Parker, J. Geophys. Res. **62**, 509 (1957).
- ³ P. Sweet, *Electromagnetic Phenomena in Cosmical Physics, International Astronomical Union (IAU) Symp.*, vol. 6 (ed B. Lehnert Cambridge Univ. Press, London, 1958).
- ⁴ H. E. Petschek, Physics of solar flares, NASA Report SP-50, Washington DC pp. 425–439 (1964).
- ⁵ B. U. O. Sonnerup and E. R. Priest, J. Plasma Phys. **14**, 283 (1975).
- ⁶ I. J. D. Craig and S. M. Henton, Astrophys. J. **450**, 280 (1995).
- ⁷ E. R. Priest, V. S. Titov, R. E. Grundy, and A. W. Hood, Proc. R. Soc. Lond. A **456**, 1821 (2000).
- ⁸ E. Tassi, V. S. Titov, and G. Hornig, Phys. Lett. A **302/5-6**, 313 (2002).
- ⁹ I. J. D. Craig and R. B. Fabling, Astrophys. J. **462**, 969 (1996).
- ¹⁰ I. J. D. Craig, R. B. Fabling, J. Heerikhuisen, and P. G. Watson, Astrophys. J. **523**, 838 (1999).
- ¹¹ C. Mellor, E. R. Priest, and V. S. Titov, Geophys. Astrophys. Fluid Dynamics **96**, 153 (2002).
- ¹² P. G. Watson and I. J. D. Craig, Sol. Phys. **207**, 337 (2002).
- ¹³ K. Schindler, H. Hesse, and J. Birn, J. Geophys. Res. **93 A6**, 5547 (1988).
- ¹⁴ E. R. Priest and T. G. Forbes, Sol. Phys. **119**, 211 (1989).
- ¹⁵ E. R. Priest, V. S. Titov, G. E. Vekstein, and G. J. Rickard, J. Geophys. Res. **99**, 21467 (1994).
- ¹⁶ E. R. Priest and V. S. Titov, Phil. Trans. Roy. Soc. Lond. A **354**, 2951 (1996).
- ¹⁷ M. Nishio, K. Yaji, T. Kosugi, H. Nakajima, and T. Sakurai, Astrophys. J. **489**, 976 (1997).